

## Sub-Master Cabinet (Surface Mount)



- 10 Zone 2500-10B
- 16 Zone 2500-16B
- 32 Zone 2500-32B
- 48 Zone 2500-48B
- 64 Zone 2500-64XB
- 80 Zone 2500-80XB
- 96 Zone 2500-96XB
- 112 Zone 2500-112XB
- 128 Zone 2500-128XB

### Dimensions:

- **2500-10B, 16B:** 15.14" H x 12" W x 6.19" D
- **2500-32B, 48B, 64XB, 80XB, 96XB, 112XB, 128XB:** 21.03" H x 20.3" W x 5.19" D

## Command Center (Desk Mount)



- 10 Zone 2500-10D
- 16 Zone 2500-16D
- 32 Zone 2500-32D
- 48 Zone 2500-48D
- 64 Zone 2500-64XD
- 80 Zone 2500-80XD
- 96 Zone 2500-96XD
- 112 Zone 2500-112XD
- 128 Zone 2500-128XD

## Sub-Master Cabinet (Flush Mount)



- 10 Zone 2500-10F
- 16 Zone 2500-16F
- 32 Zone 2500-32F
- 48 Zone 2500-48F
- 64 Zone 2500-64XF
- 80 Zone 2500-80XF
- 96 Zone 2500-96XF
- 112 Zone 2500-112XF
- 128 Zone 2500-128XF

### Dimensions:

- **2500-10F, 16F:**
  - **Front Frame:** 16.06" H x 14" W x 3.07" D
  - **Back Box:** 15.64" H x 12" W x 3" D
- **2500-32F, 48F, 64XF, 80XF, 96XF, 112XF, 128XF:**
  - **Front Frame:** 21.13" H x 25" W x 3.06" D
  - **Back Box:** 20.66" H x 23" W x 3" D

## Specifications:

- **Mounting:** Surface, flush, or desk
- **Design:** Powder coated steel enclosure with twist lock closure
- **Warranty:** 2 Years

## CODE COMPLIANCE:

- ADA, ASME A17, and B44 code compliant

## POWER & WIRING REQUIREMENTS:

- Sub-Master Stations to Distribution Module: Single pair or via IP (contact RATH® for a quote on the IP version)
- Sub-Master Stations are powered from the Distribution Module (IP based units require PoE)

## PHONE CAPABILITIES:

- Audible alert sounds when phones place a call until Base Station or Sub-Master Station joins conversation
- LEDs indicate which Call Boxes have initiated a call
- Rescue personnel can communicate with individual Call Boxes and outside party
- Calls wait in queue until previous call is disconnected

## ADDITIONAL FEATURES:

- Includes handset for communication to elevators
- Can be configured with the main Command Center and multiple Sub-Master Stations (available in desk, surface, or flush mount)