

3200 Call Commander Series

SmartCommand Two-Way Communication (Area of Refuge)



Coordinated emergency communication from one central location.

- Call boxes trigger a persistent alert until answered.
- LCD displays up to 16 calls with location and order received.
- Activation plays a message confirming an emergency.
- Calls queue if the line is busy and process automatically.
- Large buttons manage up to 128 calls.
- Sort by "Urgent" or "Not Urgent."
- Communicate with individual boxes, all boxes, or off-site teams.



Specifications

	3200D*	3200F*	3200S*
Mounting	Desk Mount	Flush Mount	Surface Mount
Dimension	7.95" H x 9.84" W x 3.03" D	16.11" H x 14" W x 3" D	15.14" H x 12" W x 6.19" D
Enclosure	N/A	Powder-coated steel enclosure with twist lock closure	Powder-coated steel enclosure with twist lock closure
Weight	2.57 lb	20.35 lb	20 lb
Phone Material	ABS – flame retardant		
Communication	Hands free speaker/microphone & control buttons		
Sound	<70 dB		
Monitoring	LCD monitoring panel		
Power Source	BOSS part #3400 (32 zone) or #3400-128 (128 zone)		
Power Rating	2.9W		
Wiring Requirements	Connect to BOSS using 18 AWG two-wire pairs (RATH™ part #RP7500094B or equivalent)		
	If local codes require a survivable path: 2 hour or CI 2 hour fire-rated cable (RATH™ part #66120 or equivalent)		
Connection	4 pin 5.08mm pluggable terminal block		
Environmental	Operating temperature: 23°F to 131°F (-5°C to 55°C), Humidity: 5-95%		
Warranty	2 years		
Code Compliance	UL 2525, NFPA 72 2022, NFPA 101 2024, IBC/IFC 2024 and ADA		

*Works with SmartCommand System: 3400 BOSS, 3300 Call Boxes, and 1000 UPS Power Supply.

AVIRE

N56 W24720 N. Corporate Circle Sussex, WI 53089
800-451-1460 | sales.us@avire-global.com
avire-global.com/en-us