

3400 BOSS Series

SmartCommand Two-Way Communication (Area of Refuge)



The "Brains" of the SmartCommand System.

- Centrally configures call boxes, including text-to-speech announcements and address settings.
- Redirects calls up to two emergency phone numbers via a dedicated phone line.
- Powers the Call Commander and all connected call boxes.
- Supervises power, phone line status, and call box integrity.
- Compatible with most alarm and fire panels.
- Includes relay outputs for system faults and activations.



Specifications

| | SmartCommand BOSS - 3400 | SmartCommand BOSS 3400-128 |
|---------------------------------------|--|----------------------------|
| Maximum Number of Call Boxes | 32 | 128 |
| External Phone Lines | 1 | 2 |
| Daisy Chain Loops | 2 | 4 |
| Wiring Limitation Total Loop Length | 4750 ft | |
| Wiring Limitations Between Call Boxes | 950 ft | |
| Wiring Limitations to Call Commander | 900 ft | |
| Wiring | All loop connections: 18 AWG 2 pair cable system (RP7500094B) or 2 hour fire-rated (#66102 - 550 ft. or #66120 - 1000 ft.) IO ports to battery. 2 single pair battery, 3 wire if going to fire system (not provided). PSTN (external line) - 1 pair cable system | |
| Power Consumption | 10 W (1 call box) 27 W (32 call box) 74 W (128 call box) | |
| Supply Voltages | 120V 60 Hz VAC | |
| SPDT Relay Contact Rating | 16A at 250 VAC / 24 VDC, 0.3A at 300 VDC | |
| Opto-isolated Input Rating | 12 V - 230 V (AC & DC) | |
| Backup Requirements | Battery backup (RATH part #1000) Standby - 24 hours minimum; Active talk time - 5 minutes | |



Rev Sep 25

AVIRE

N56 W24720 N. Corporate Circle Sussex, WI 53089
800-451-1460 | sales.us@avire-global.com
avire-global.com/en-us

Specifications Continued

| | |
|---------------------------------|--|
| | Smart Command BOSS - 3400 Smart Command BOSS 3400-128 |
| Connections | Call Commander L1A: 4-pin 5.08 mm pluggable terminal block Call Box: 4-pin 5.08 mm pluggable terminal block External line: 2-pin 5.08 mm pluggable terminal block Power: 3-pin female connector EC C13 Opto-Isolated Inputs: 2-pin 5.08 mm pluggable terminal block Relay Outputs: 3-pin 5.08 mm pluggable terminal block Configuration: USB type B |
| Supervision | Primary power Secondary power Telephone line Loop monitoring |
| Code Compliance | UL 2525, NFPA 72 2022, NFPA 101 2024, IBC/IFC 2024 and ADA |
| Dimensions | 17.20" W x 12.59" D x 3.46" H (437 mm x 320 mm x 88 mm) |
| Material | Powder-coated steel |
| Weight | 10.28 lbs |
| Mounting | Surface Mount, Wall Mount (brackets included), or Rack Mount (brackets included, fits standard 19" network rack) |
| Environmental | 23°F to 131°F (-5°C to 55°C), 5-95% humidity |
| Programming Requirements | Requires a laptop to program (USB type B cable included) |
| Warranty | 2 years |

Compatible with SmartCommand System Components:

3200 Call Commander Series, 3300 Call Boxes, and 1000 Uninterruptible Power Supply

Diagram

