

SAFE-AN-1002

Remote Annunciator



Remote system monitoring and alerts for Public Safety DAS.

- Connects to all RATH® BDAs and head-end systems.
- Visual and audible alerts notify personnel of system issues.
- Single CAT5 cable supports power and alarm connectivity.
- Magnetic switch simplifies testing and alarm muting.
- Form-C relays support external notifications and fire panel connections.
- Compliant with NFPA and UL requirements.



Specifications

Front Panel Dimensions	6.50" x 5.75" x 0.08"
Recessed Gang Box Dimensions	4.50" x 4.50" x 3.00"
Enclosure	NEMA 4
Mounting	Recessed or Flush
Max Distance from BDA	1,000 ft
Power	Provided by the BDA
Connection	4-Pair 24 AWG CAT 5 Cable, RJ45 Connector

**Tested using 4 pair, 24AWG CAT5 wire, model 5ECMRWHT_1kbx CAT5E riser cable from TrueCable(TM). Test prior to installation.*

AVIRE

N56W24720 N Corporate Cir., Sussex, WI 53089
800-451-1460

sales.us@avire-global.com

avire-global.com/en-us